

BATTERY CHARGER DATASHEET

AX2 SMART CHARGER

axcell[®]
Energy Solution



VOLTAGE

6V/12V

CHARGING CURRENT

2A

STAGES

8 LEAD ACID / **3** LITHIUM

BATTERY

2Ah > 40Ah

The AX2 is a smart battery charger & maintainer designed for all powersport batteries. With dedicated programs for lead-acid and lithium batteries, the AX2 is a 6V and 12V battery charger rated at 2A with battery capacity up to 40Ah. Safe and easy to use, the 8 steps of charge will ensure maximum performance and lifetime for all your batteries.

SPECIFICATIONS

- > **Type:** Automatic
- > **Input voltage range:** 100-240Vac
- > **Input frequency:** 50-60Hz
- > **Max output voltage:** 6/12V
- > **Charging current:** 2A
- > **Housing material:** ABS
- > **Dimensions:** 154x72x41mm
- > **Weight:** 0.28kg

BENEFITS

- > Charges & maintains 6V-12V lead acid batteries (GEL, AGM, MF, DRY, CA/CA, WET) & LiFePO4 batteries
- > 2A charging current with battery capacity up to 40Ah
- > 4 charge modes
- > Easy to set up and use: connect, select a charge mode & forget
- > Easy to read LED display
- > Fully protected against short circuit, wrong connections, overcharge and overheat
- > Delivered with 1 clamp set and 1 eyelet terminals set

BOX CONTENT

- > AX2 Charger with quick connector (88cm)
- > 1x eyelets terminal set (50cm)
- > 1x clamp set (50cm)
- > 1x user manual

